

IC-F310S IC-F410S



- **Simple operation with up to 8 channels**

Up/down switches for volume and channel selection with LED's that indicate the selected operating channel.

- **Flexible setup**

Four programmable switches give access to a variety of functions and can be assigned functions for specific applications.

- **Durable construction**

The highly dependable diecast aluminum chassis and polycarbonate front panel are resistant to impact.

- **Multiple signalling systems**

CTCSS and DTCS encoder/decoder are standard; 2-tone/5-tone encoder (decoder optional) and SmarTrunk II™ capability*. *Optional UT-105 SmarTrunk II™ Logic Board is required; SmarTrunk II is a trademark of SmarTrunk Systems Inc.

- **Optional voice scrambler**

Provides higher communication privacy. Up to 1020 scrambling codes (4 groups x 255 codes) with divided frequency rolling system, or 32 scrambling codes are available with optional UT-110 or UT-109, respectively.

- **Selectable channel spacing**

Wide and narrow switching is available for each channel independently (12.5/25 kHz).

- **Advanced PC programming package**



ADDITIONAL FEATURES

- Voice scrambler on/off (optional UT-109/UT-110 required)
- Backlit keys for night operation
- Emergency call with single and repeat function
- Automatic ID transmission linked to PTT
- 51 frequencies for CTCSS (plus 1 programmable)
- Polarity selectable for DTCS
- Autodialing memory for DTMF
- Emergency and log/ID memories available
- 2 priority channels
- Normal and priority scan
- Scan start at power on
- Automatic scan start and/or receive mute when mic. is on hook
- CTCSS reverse burst
- Automatic priority channel selection and/or mute release when mic. is off hook
- Optional PIN code input to prevent operation by unauthorised persons
- Programmable minimum level for audio output
- Talk around function (temporary simplex operation on a duplex channel)
- Time-out timer
- Time-out ID transmission
- Penalty timer
- Transmit lockout (channel busy / repeater / reverse repeater)
- 2 selectable 'stun' functions (optional UT-96 required)
- Compact body provides easy installation

SPECIFICATIONS

GENERAL

- Frequency coverage* :

IC-F310S	136-155 MHz	146-174 MHz
IC-F410S	400-430 MHz	440-470 MHz
	470-490 MHz	490-520 MHz
- Number of channels* : 8 ch or 4 ch x 2 banks
- Type of emission :

16K0F3E (25 kHz; wide)
8K50F3E (12.5 kHz; narrow)
14K0F3E (20 kHz; middle)
- PLL channel step : 5 kHz and 6.25 kHz
- Frequency stability : ±1.5 kHz
- Operating temp. range : -20°C to +55°C
- Power supply voltage : 13.2 V DC (negative ground)
- Current drain :

Tx at 25 W	7 A
Rx max. audio	700 mA
standby	200 mA
- Antenna connector : SO-239 (50 Ω)
- Dimensions : 140(W)×40(H)×170(D) mm
- Weight : 1.2 kg

TRANSMITTER

- Output power : 25 W (10 W for Italy, 6 W for IC-F310S German ver.)
- Modulation system : Variable reactance freq. mod.
- Max. freq. deviation : ±5.0 kHz (wide) ±2.5 kHz (narrow) ±4.0 kHz (middle)
- Spurious emissions : 0.25 µW
- Adjacent ch. power : 70 dB (wide/middle) 60 dB (narrow)
- Mic. connector : 8-pin modular (600 Ω)

RECEIVER

- Intermediate freq. : 1st 31.05 MHz (IC-F310S) 46.35 MHz (IC-F410S) 2nd 450 kHz
- Sensitivity : -4 dBµV (amt. IC-F310S) -2 dBµV (amt. IC-F410S)
- Squelch sensitivity : -4 dBµV (IC-F310S) -2 dBµV (IC-F410S)

- Adj. ch. selectivity : 70 dB (wide/middle) 60 dB (narrow)
- Spurious response : 70 dB
- Intermodulation : 65 dB
- Audio output power : 3.5 W at 10% distortion/4 Ω load
- Ext. SP connector : 2-conductor 3.5 (d) mm (16")/4 Ω

Supplied Accessories

- Hand mic.* ○ DC power cable ○ Fuses
- Mounting bracket kit ○ Key assign stickers

*Varies according to version.

Measurements made in accordance with ETS 300 086. All stated specifications are typical and subject to change without notice or obligation.

OPTIONS

- **UT-96 5-TONE UNIT**
Provides 2-tone and 5-tone decoder capabilities
- **UT-105 SmarTrunk II™ Logic Board***
Provides SmarTrunk II™ capabilities.
*SmarTrunk II is a trademark of SmarTrunk Systems Inc.
- **UT-109/UT-110 VOICE SCRAMBLER UNITS**
Provides operating security. Ask your dealer for details about usable version, etc.
UT-109: Non-rolling type. UT-110: Rolling type.
- **OPC-617 ACC CABLE**
For external terminal connection.
- **SP-5/SP-10/SP-22 EXTERNAL SPEAKERS**
Compact and easy-to-install.
Input impedance: 4 Ω; Max. input power: 5 W
- **HM-100/T HAND/DTMF MICROPHONE**
Supplied microphone. Varies with version.

UT-96



SP-10



SP-22



OPC-617



Icom Inc. 6-9-16, Kamihigashi, Hirano-ku, Osaka 547-0002, Japan Phone: 06 6793 5302 Fax: 06 6793 0013

Count on us!

Icom America Inc.

Corporate Headquarters
2380 116th Avenue N.E., Bellevue, WA 98004, U.S.A.
Phone: (425) 454-8155 Fax: (425) 454-1509
URL : <http://www.icomamerica.com>
Customer Service
Phone: (425) 454-7819

Icom Canada

3071 #6 Road, Unit 9, Richmond, B.C., V6X 2T4, Canada
Phone: (604) 273-7400 Fax: (604) 273-1900
URL : <http://www.icomamerica.com>

Icom (Australia) Pty. Ltd.

A.C.N. 006 082 575
290-294 Albert Street, Brunswick, Victoria, 3056, Australia
Phone: 03 9387 0666 Fax: 03 9387 0322
URL : <http://www.icom.net.au>

Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road, Taipei, Taiwan, R.O.C.
Phone: (02) 2559 1869 Fax: (02) 2559 1874

Icom (Europe) GmbH

Communication Equipment
Himmelsgarten Str. 100, D-40225 Düsseldorf, Germany
Phone: 0211 348047 Fax: 0211 333639
URL : <http://www.icomeurope.com>

Icom Spain S.L.

Ctra. de Gracia a Monrea Km. 14,750
06190 Sant Cugat del Valles Barcelona, SPAIN
Phone: (93) 590 26 70 Fax: (93) 589 04 46
URL : <http://www.icomspain.com>

Icom (UK) Ltd.

Unit 9, Sea St., Heme Bay, Kent, CT6 8LD, U.K.
Phone: 01227 741741 Fax: 01227 741742
URL : <http://www.icomuk.co.uk>

Icom France SA

Zac de la Plaine, Rue Brindejonc des Moulinais
BP 5604, 31505 Toulouse Cedex, France
Phone: 561 36 03 03 Fax: 561 36 03 00
URL : <http://www.icom-france.com>



Certificate Number D14100

Icom Inc. (Japan), is an
ISO9001 certification
acquired company.

Your local distributor/dealer:

Point electronics

A- 1060 Wien, Stumpergasse 41 - 43
Tel.: +43/ 1/ 597 08 80/0 FAX: DW 40
www.point.at mail@point.at